



ME100SV

ME200BK

## REMOTE LINK™ Infra Red Sensors

- Watch and change channels in extra rooms using SKY™ remote handset
- Compatible with all IR pass amplifiers
- Inconspicuous design
- ME200 designed for LCD / Plasma flat screen televisions

### PRODUCT RANGE

- ME100 BK - Black Infra-Red IR sensor
- ME200 BK - Black LCD/Plasma TV Infra-Red IR sensor
- ME100 SV - Silver Infra-Red IR sensor
- ME200 BKB - Black LCD/Plasma TV Infra-Red IR sensor (Bulk packed)

### TECHNICAL SPECIFICATION

	ME100BK	ME100SV	ME200BK	ME200BKB
Standard /Flat Screen TV	✓	✓	-	-
LCD/Plasma Screen TV	-	-	✓	✓
Colour	Black	Silver	Black	Black
Frequency	45-862MHz	45-862MHz	45-862MHz	45-862MHz
Return Path Frequency	5-30MHz	5-30MHz	5-30MHz	5-30MHz
Insertion Loss	<1dB	<1dB	<1dB	<1dB
Control Commands	6MHz Carrier 38 KHz pulse			
Power required	9V DC15mA			
Impedance	75Ω			
Sensor Lead length	900mm			
Connectors	IEC60169-2(f) female coax socket			
Connectors	IEC60169-2(m) male coax plug on 245mm fly lead			